



**SKY6026 120/60 watt 11-Position Stereo Volume Control (White)  
In Weather-Resistant Outdoor Box**

The SKY6026 features excellent sound quality with virtually no high- or low-end roll-off, a non-shorting design which prevents amplifier damage, color-coded right angle solderless speaker terminals with easy top termination. All volume control sets include a metal bracket plate, color-coded plastic insert, color-coded knob, wall plate and mounting screws. The 11-position switch offers 36dB of attenuation with Off, (2) 6dB, (7) 3dB and Full-On settings.

**Installation Instructions:**

Installation is fairly simple, but there are a few issues you should consider before and during installation:

- Route the cable into the weather-proof box in a manner which allows for easy access to the connectors on the control. Note that all the control's connectors are at one end.
- Make sure to use the integral strain reliefs where appropriate when routing the cable into the weather-proof box.
- Leave enough slack cable in the weather-proof box to ensure easy connection to the volume control.
- Mark the input and output cables accordingly to eliminate confusion during the final installation.
- Strip each of the (8) individual wires (4 from the amplifier and 4 to the speakers). To avoid a short, do not strip the wires more than ¼ inch.
- Using a #1 flat-blade screwdriver, insert the appropriate wires into the connectors and tighten securely.
- Carefully insert the control into the weather-proof box making sure that no wires are pinched. Note that the design of the control allows the cables to exit from the top side of the connector.